

LCD133-070CTL1NCNTTR1.0

7" WUXGA

In-Cell Touch

1200*1920

www.lincolntechsolutions.com ©2021 All rights reserved.

Rev.1.4

lincolntechsolutions.com • 1155 Kildaire Farm Road, Suite 100 • Cary, NC 27511

. ?
Table of Contents
Revision History
Document Revision
Hardware Revision
General Specifications
Block Diagram
Pin Out-LCD
Absolute Max Ratings - LCD
Absolute Max Ratings – PCAP - In Cell Touch
Electrical Characteristics - LCD
Electrical Characteristics – PCAP - In Cell Touch
Backlight Specifications
Timing Specifications - LCD
Timing Specifications – PCAP
Optical Characteristics
Packaging
Quality & Inspection Criteria
Terminologies:
Inspection Conditions
Acceptance Criteria Table:
Appendix 1: Drawing
\sim

Revision History

Document Revision

Revision H	listory	
Document Re	vision	
Date	Version #	Description
Date		Description
1/24/2020	R1.0	Preliminary Release
1/29/2020	R1.1	Updated Temp Specs
4/27/2020	R1.2	Updated pinout
12/17/2020	R1.3	High Resolution Drawing addition, packaging added, backlight power chart added
2/3/2020	R1.4	Temperature typo corrected from -10 to -20 on page 8. Uniformity updated to 5 points. Backlight description added.

Hardware Revision

Date	Version #	Description
12/23/2019	R0.1	Preliminary Release
1/24/2020	R1.0	Production

General Specifications

Item	Specification	Unit
Outline Dimensions	108.52(W) X 171.70(L) X 3.505(H)	mm
Display Size	7.02	inches
Active Area	94.5 X 151.2	mm
Pixel Pitch	0.07875 X 0.07875	Smm
Number of Dots	1200 X 1920	-
LCD Туре	ADS 10 bit (8bit + 2bit FRC)	-
Backlight Type	LED White	-
Viewing Direction	Free	-
Touch Panel	Capacitive Touch (In-Cell) – FT7250	-
Luminance	600	cd/m^2
Interface	MIPI	-
Surface Treatment	Generic cover glass	-
Operating	-20 to +70	°C
Operating		



Pin Out-LCD

The interface connector is a 40 pin Zif with 0.5mm pitch. It accepts an FFC of 0.3mm thickness and gold-plated contacts. An example of the part mounted on the LCD flex is, Hirose FH28-40S-0.5SH(05)

Number	Pin Name I/O		Description
1	NC	-	No connection – Must not connect
2	IOVCC	Р	Power supply for system (1.8V)
3	IOVCC	Р	Power supply for system (1.8V)
4	GND	Р	Ground
5	LCD_RSTN	Ι	LCD reset signal, Active Low
6	NC	-	No connection
7	GND	Р	Ground
8	MIPI_0N	Ι	MIPI Negative data inputs
9	MIPI_0P	Ι	MIPI Positive data inputs
10	GND	Р	Power ground
11	MIPI_1N	I	MIPI Negative data inputs
12	MIPI_1P		MIPI Positive data inputs
13	GND	Р	Power ground
14	MIPI_CKN	Ι	MIPI Negative clock inputs
15	MIPI_CKP	Ι	MIPI Positive clock inputs
16	GND	Р	Power ground
17	MIPI_2N	Ι	MIPI Negative data inputs
18	MIPI_2P	Ι	MIPI Positive data inputs
19	GND	Р	Power ground

20	MIPI_3N	Ι	MIPI Negative data inputs						
21	MIPI_3P	Ι	MIPI Positive data inputs						
22	GND	Р	Power ground						
23	TP_SCL	Ι	TP I2C Clock 1.8V						
24	TP_SDA	I/O	TP I2C Data 1.8V						
25	GND	Р	Power ground						
26	TE	0	Tear output						
27	PWMO	0	PWM control signal for LED driver (CABC)						
28	TP_INTN	0	Touch Interrupt 1.8V, Active Low						
29	TP_RSTN	Ι	TP reset signal 1.8V, Active Low						
30	GND	Р	Power ground						
31	LED-	Р	LED Cathode						
32	LED-	Р	LED Cathode						
33	NC	-	No connection						
34	VSN	Р	Analog supply negative voltage (-5~-6V)						
35	VSN	Р	Analog supply negative voltage (-5~-6V)						
36	NC	-	No connection						
37	VSP	Р	Analog supply positive voltage (5~6V)						
38	VSP	Р	Analog supply positive voltage (5~6V)						
39	LED+	Р	LED Anode						
40	LED+	Р	LED Anode						

Absolute Max Ratings - LCD

Item	Symbol	Value	Unit
Power Supply Voltage for Logic	IOVCC	-0.3 - 4.5	v ç O
Power for Analog Negative	VSN	0 ~ -6.6	
Power for Analog Positive	VSP	0 ~ +6.6	<u> </u>
Operating Temperature	Topr	-20 to 70	0 ℃
Storage Temperature	Tstg	-30 to 80	S°C

Absolute Max Ratings – PCAP - In Cell Touch

Item	Symbol	Value	Unit
Power Supply Voltage for Logic	vcc	-0.3 – 3.47	V
Signal IO	VCC IO	-0.3 – 3.47	V

Electrical Characteristics - LCD

Item	Symbol	Min	Тур	Мах	Unit	Test Condition
Operating Voltage	IOVCC	1.65	1.8	1.95	V	-
Voltage for Analog Negative	VSN	-6.5	-5.5	-4.5	V	-
Voltage for Analog Positive	VSP	4.5	5.5	6.5	V	-
Supply Current	IDD(IOVCC)	-	-	50	mA	Ta = 25 °C

www.lincoIntechsolutions.com

©2021 All rights reserved.

Supply Current	IDD(VSN)	-	-	75	mA	Ta = 25 °C
Supply Current	IDD(VSP)	-	-	75	mA	Ta = 25 °C
	Vih	0.7IOVCC	-	IOVCC	V	
Input Voltage	Vil	0	-	0.3IOVCC	V	XO'
Input Leakage Current	IiL	-1.0	-	1.0	μA	Vin = IOVCC

Input Leakage Current	IiL	-1.0	-	1.0	μΑ	Vin = IOVCC
				- S	co	
Electrical Characte	ristics – PC	AP - In Ce	ell Tou	ch		
Item	Symbol	Min	Тур	Мах	Unit	Test Condition
Operating Voltage	VCC	1.65	1.8*	3.3	V	-
Operating Voltage IO	VCC_IO	1.8	1.8*	3.3	V	
Supply Current	IDD(VCC)	3	8	14.5	mA	Ta = 25 °C
Input Voltage	Vih	0.7VCC_IO	-	VCC_IO	V	-
	Vil	GND	-	0.3VCC_IO	V	-

*IOVCC powers the PCAP circuitry which is powered at 1.8V

www.lincoIntechsolutions.com ©2021 All rights reserved.

incoln

Backlight Specifications

Typical drive current is suggested as 80mA. It may be possible to drive the individual LEDs beyond its typical of 20mA (per LED) if thermals are mitigated in the integration of the LCD. Wattage vs NITS is provided for reference to show the linearity of NITS.

Item	Symbol	Min	Тур	Max	Unit	Test Condition
Supply Voltage	Vf	-	28.0	-	O Y	If = 80mA
Supply Current	If	-	80	- (mA	NITS = 600
Backlight Color			Whi	ite		
3 2.5 2 1.5 1		attage vs NI	TS (1.89	2.31	2.74	
	200 30	00 400 NITS	500	600	700	

Timing Specifications - LCD

Refer to Focal Tech FT7250

Timing Specifications – PCAP



Symbol	Parameter	Min	Тур	Max	Unit
f _{SCLK}	SCL clock frequency	10	-	400	kHz
T _{LOW}	SCL clock LOW period	1.2	-	-	us
T _{HIGH}	SCL clock HIGH period	0.6	-	-	us
T _{SU;DATA}	Data set-up time	250	-	-	ns
T _{HD;DATA}	Data hold time	0	-	0.9	us
Tr	SCL and SDA rise time	20	-	300	ns
T _f	SCL and SDA fall time	20	-	300	ns
T _f	SDA fall time for read out	20	-	1000	ns
C _b	Capacitive load represented by each bus line	-	-	400	pF
T _{SU;STA}	Setup time for a repeated START condition	0.6	-	-	us

www.lincolntechsolutions.com

©2021 All rights reserved.

Symbol	Parameter	Min	Тур	Max	Unit
T _{HD;STA}	START condition hold time	0.6	-	-	us
T _{SU;STO}	Setup time for STOP condition	0.6	-	-	us
T _{sw}	Tolerable spike width on bus	-	-	50	ns
T _{buf}	BUS free time between a STOP and START condition	4.7	-	0,0	us
			il ⁰¹		
		30.			
	echsolutions.com	3			

x O

Optical Characteristics

All measurements taken after minimum runtime of 25 minutes.

	Item				Specificatio		5	
Item		Symbol Conditions		Min Typ Max		• Unit	Note	
Response Time		Tr Tf	Ta = 25°C	_	25	-	ms	(1)(4)
ontrast Ratio		CR	Normal Viewing Angle	1200	·	S	-	(1)(3)(5)
	Hor.	X-		70	80	-	Deg	(3)(5)
Viewing Angle	HUI.	Х+	CR>10	70	80	-	Deg	
	Ver.	Y+		70	80	-	Deg	
		Y-		70	80	-	Deg	
	Red	Rx	S	-	.6583	-	-	
	Red	Ry		-	.3433	-	-	
	Green	Gx	07	-	.29	-	-	
Chromaticity		Gy	05	-	.6362	-	-	
Chromaticity	Blue	Bx	Ta = 25 °C	-	.1517	-	-	
		Ву		-	.0876	-	-	
	White	Wx		-	.2911	-	-	
	XQ	Wy		-	.3231	-	-	
Luminance		L	Ta = 25 °C	-	600	-	cd/m2	(1)
70	Color G	amut Ratio N	ITSC	-	75	-	%	
Uniformity		U		75	80	-	%	(2)

Note 1: Measurement setup

The LCD module should be stabilized at a given temperature for 25 minutes to avoid abrupt temperature change during measurement. After temperature saturation measurement should be executed.



Brightness uniformity = (Minimum Luminance of 5 points / Max Luminance of 5 points) * 100



Note 3: Viewing Angle

Definition of viewing angle for Y+/- and X+/- is as follows.



Note 5: Contrast Ratio

Definition of Contrast Ratio is as follows.

on technology solutions confidential Contrast measurements shall be made at a viewing angle of 0° at the center of the surface.

CR =

www.lincoIntechsolutions.com ©2021 All rights reserved.

incoll



Quality & Inspection Criteria

Terminologies:

LCD: Liquid Crystal Display; Each pixel contains three dots of R, G, and B (sub-pixel).

Bright Dot: 1 sub-pixel is a dot. Defects should be larger than 1/2 of a sub-pixel. Dots that are not visible through a 5% ND filter or smaller than 1/2 of sub-pixel size will not be counted as a dot defect.



Dark Dot: Any single sub-pixel that does not light up in a white screen or another non-black screen is called a dark dot.



incol

Yer

Two adjacent dots (horizontal direction): Use the bright dot illustration as an example to demonstrate two horizontal consecutive dots.



Two adjacent dots (vertical direction): Use the bright spot illustration as an example to demonstrate two vertical consecutive dots.



Two adjacent dots (bevel direction): Use the bright spot illustration as an example to demonstrate two consecutive dots in the bevel direction.



Three or more adjacent dots (horizontal): Use the bright spot illustration as an example to demonstrate three or more consecutive horizontal and vertical dots.

R	G		В	R	G	В	R	G	В	R	G	E	3	R	G	В	R	G	В	RO
R	G	1	В	R	G	В	R	G	В	R	G	E	3	R	G	В	R	G	¢В	\mathbf{O}
R	G		В	R	G	в	R	G	В	R	G	E	3	R	G	В	R	G	В	
R	G	[В	R	G	В	R	G	В	R	G	E	3	R	G	В	R	G	B	
R	G	F	В	R	G	В	R	G	В	R	G	F	З	R	G	В	R	G	В	
	0				0	D					0				0			0		
Illus	tratio	on of	`spa	cing	betwo	een t	wo d	ots: (]	Distanc	e is th	e rela	tive	dist	ance	betwo	een th	e X-ax	es of	the tv	wo dots
or the	e rela	tive	dista	nce b	oetwe	en th	e Y-a	ixes of	the tw	C	, wiii	chev		starg	er)					Dista Y-axe
or the	e rela	B	dista R	nce b	B	R R	e Y-a		R G	B	ĉ	G	B	R	G	В	R			Distance Y-axes o
or the	e rela	tive						BF		C	C		2			B B	٦			Distance b Y-axes of t
or the	e rela G	B	R	G	В	R	G	BF	R G	C B	R	G	В	R	G		R		‡	Distance betw Y-axes of the
or the R R	G G	B B	R R	G	B B	R R	G G	B F B F	R G	B B	R R R	G	B	R	G G	В	7		\$	Distance betwee Y-axes of the two
or the R R R	G G G	B B B	R R R	G G G	B B	R R R	G G G	B F B F		B B B	R R R R	G G G	B B B	R R R	G G G	B B	R		\$	Distance between the Y-axes of the two dots

Functional Test

The LCD display testing program should display the following screens in order: all red, all green, all blue, all white, all gray, all black.

Inspection Requirements

After booting the system (single illumination), there are no non-display, unlit backlight, dark backlight, blinking, or other abnormal signs, and there are no bright lines, dark lines, or bright rims/leakage of light close to the LCD bezel.

fildenti

Newton's Ring



Under high temperature and high humidity conditions, uneven deformations caused by heat in different layers of the LCD module will result in the display of an all-white screen. However, this condition can be recovered when temperature is resumed under normal circumstances. A specific determination can be conducted according to the operating conditions and storage conditions defined in the product's technical specifications. Any exception will be negotiated and mutually agreed by both parties. (Ripples are not permitted at fixed locations. For ripples at non-fixed locations, they are OK if they disappear within two seconds.)

LCD blaze

Uneven internal LCD installation, surface detormation of the LCD polarizer, internal structural interference of the LCD module, damaged LCD backlight plates, and other factors may cause partial fading of color on the LCD display. When observed from a certain incident angle (upper 10°, lower 3°, 40° on both sides), they will appear as white cicatrices, typically about the size of a grain of rice. In serious cases, they accumulate in large patches or stripes, appear in different degrees under various colors (red, blue, green, black, gray, white), and are especially obvious under an all-gray screen. Blazes with diameters \geq 0.5mm are not allowed: for those with diameters under 0.5 mm, 2 are acceptable if the space between them is \geq 15mm. Card chromatic aberration ratio versus ND Filter: 1.0 + 0.3 standard = 5% ND Filer (see definition of Mura).

Mura

Mura refers to the unevenness and irregularity that is visible in the image. It is difficult for visual inspection to recognize the non-uniform brightness or mura. Mura detection is subjective and therefore doesn't have pass/fail criteria. There are several precautions to take which can avoid mura. Avoid high ambient temperatures around the module, frame warpage and high temperature operation over long periods of time. Utilize screen savers to avoid mura.

 $30 \text{ cm} \sim 40 \text{ cm}$

90°

Inspection Conditions

Inspection distance should be 35cm \pm 5cm with a FujiFilm ND-LCD 5% filter approximately 5cm from the backlight surface.

 $30 \text{ cm} \sim 40 \text{ cm}$

5mm

jtions

Viewing angle: 90° ± 5°.

Room temperature: 23+/- 2°C

Humidity: 60 +/- 10%

Inspection Ambient Illumination: 300-700 LUX

Viewing Distance: 30-40 CM



ND Filter

incl

Acceptance Criteria Table:

There should be no corrosion or cracking, or an uneven coating layer on LCD display surface, and there should be no sign of coagulation, flaking, cracking, or wear. The definition of minor defects and acceptance criteria are shown in the following table:

Item	Size	Unit	Acceptance qty.
	W < 0.05	mm	Ignore
Unfelt scratch visible with backlight off.	W > .05 and < .10 L > .3 and < 3.0	mm	4
	W > .10 or L > 3.0	mm	none
	Visible with ba	acklight on	none
Felt scratch		None allowed	
	D < .2	mm	Ignore
	D > .2 and < .5	mm	5
Dent visible with backlight off	Spacing bet	ween defects must be	> 30mm
	D > .5	mm	none
G	Visible with ba	cklight on	none
<u>Ze</u>	D < .2	mm	Ignore
	D > .2 and < .5	mm	5
Bubble visible with backlight off	D > .5	mm	none
, ,	Visible with ba	cklight on	none
	W < .05		Ignore

Item	Size	Unit	Acceptance qty
		mm	.0
Foreign material (line shape)	W > .05 and < .10 L > .3 and < 2.0	mm	
visible with backlight on	W > .10 or L > 2.0	mm	none
	D < .2	mm	Ignore
Foreign material (dot shape) visible with backlight on	D> .2 and < .5	mm	5
	D > .5	mm	none
	1 dot	-	4
Bright dot defect(lit)	2 adjacent dots		0
0	1 dot	-	5
Dark dot defect (not lit)	2 adjacent dots	-	2
SIL	3 adjacent dots	-	0

Page timeon technology solutions confidential www.lincoIntechsolutions.com ©2021 All rights reserved.

